

## Chicago Low Profile Exit Sign



### FEATURES

- Metal exit sign for commercial or light industrial applications
- Designed to meet the city of Chicago specifications
- White, 22 gauge steel housing with translucent glass diffuser
- Universal end/ceiling/wall mount and included matching canopy
- Long life incandescent lamps exceed brightness and uniformity requirements
- Full length directional arrows; 6" letters with 3/4" stroke
- Maintenance-free lead-acid battery with fully automatic charger
- Temperature range: 20°C to 30°C (68°F to 86°F)
- UL 924 Listed; City of Chicago approval #9823

### ORDERING INFORMATION

<b>CMX</b>				
<b>MODEL</b>	<b>FACES</b>	<b>OPERATION</b>	<b>OPTIONS</b>	
CMX	S Single D Double	Blank AC Only E Emergency	<b>277V</b> 277 VAC operation <sup>1</sup> <b>DC6</b> 6 VDC emergency socket and lamp <sup>1</sup> <b>DC12</b> 12 VDC emergency socket and lamp <sup>1</sup> <b>B</b> Black finish <b>FL</b> 7 watt fluorescent AC lamps <b>FAP</b> Fire alarm panel interface <sup>2,3,4</sup> <b>AF</b> Audible flasher alarm <sup>3,4,5</sup> <b>PH</b> Phosphorescent glass diffuser panel	

  

EXIT LEGEND	
Single face models	Double face models
3 "EXIT" (no arrows)	18 "EXIT" (no arrows)
6 "EXIT" (right arrow)	21 "EXIT" (right/left arrow)
9 "EXIT" (left arrow)	24 "EXIT" (double arrow)
12 "EXIT" (double arrow)	17 "STAIRS" (no arrows)
2 "STAIRS" (no arrows)	20 "STAIRS" (right/left arrow)
5 "STAIRS" (right arrow)	23 "STAIRS" (double arrow)
8 "STAIRS" (left arrow)	
11 "STAIRS" (double arrow)	

<sup>1</sup> For use with AC models only.  
<sup>2</sup> Operates with 24-volt AC or DC fire alarm panels.  
<sup>3</sup> FAP and AF options may not be specified together.  
<sup>4</sup> FAP and AF options not available with fluorescent lamp models.  
<sup>5</sup> AF option for use with emergency models only.

### ACCESSORIES

MODEL	DESCRIPTION
CKW	Canopy mounting kit (white)
CKB	Canopy mounting kit (black)
PMKW	18" Pendant mounting kit (white)
PMKB	18" Pendant mounting kit (black)
WG-MLT	Wire guard (wall mount - AC models)
WGTW	Wire guard (wall mount - emergency models)
WGTC	Wire guard (ceiling/end mount - AC and emergency models)

### POWER CONSUMPTION

	INCANDESCENT MODELS	FLUORESCENT MODELS
AC Only Exits	40W	18W
Emergency Exits	50W	28W

### ELECTRONICS

- Transformer isolation, surge, transient, and low voltage disconnect protection
- Reverse polarity, short circuit, brownout and AC lockout protection
- 120/277VAC 60Hz operation, test switch and LED AC-On indicator light

